

SVK-64

3 Axis Joystick Keyboard



The Veilux SVK-64 Controller(w/ Joystick) features a slick, useful design that is perfect for the remote control of CCTV Devices. This flexible unit can control up to 255 CCTV Receivers! This unit is used primarily for PTZ Cameras. The Joystick is great for controlling PTZ' movemnt as it works off of 3 Axis. The Device also comes with a built-in back light for the LCD window.

Key Features

- Controller For The Remote Control of CCTV Devices: Power, Pan / Tilt / Zoom Lens, AUX
- Controls Up To Maximum 255 CCTV Receivers
- Preset Control: 64 Positions Memory Set for each Camera
- Built-In Requital Ability For Electricity Failure: Power, Auto, Pan, Preset Position
- Built-In Back Light For LCD Window
- 3-Axis Joystick Control To Pan / Tilt / Zoom Movement
- Can Be Connected With Up to 8 Sub-Keyboards

Specifications

SVK-64

Specifications	SVK-64
Display	2 Lines by character LCD
Joystick	3 Axis
Lens control	Zoom, Focus, Iris, Pan, Tilt, Aux, Preset
Protocols	Pelco-D, Pelco-P, Factory
Devices supported	255 Cameras
Baud Rate	1200, 2400, 4800, 9600 bps
Communication Method	RS-485 (422)
Connector	RS-485 Modular Cable Connection with Junction Box Power Supplied Via Junction Box
Function Key	8
Preset position	128 points
Connector	Modular Cable Connection with Junction Box Power Supplied Via Junction
Package	Junction Box, 5M Cable (Modular Jacks Both Ends)
Operating Distance	Max 1.2Km (When Using Shielded Twisted Pair Cable)
Power	12W
Operating Temperature	32°F ~ 104°F (0°C ~ 40°C)
Weight	7.71 (3.5Kg)
Dimension	337.5(W) x 50(H) x 153(D)mm

Diagram

